



DESCRIPTION

Description

Single zone audio surveillance system designed to connect directly to an audio recorder, video recorder, CCTV monitor (with a built in speaker), remote monitoring equipment, etc.

Kit Includes

- Pre-amplified microphone.
- Interface adapter.
- 12 VDC AC adapter.
- 3' RCA Patch cable.
- Warning label.

Wiring Requirements

- Stranded 22-gauge, 2-conductor shielded cable. Distances up to 1500'.

Caution

It may be against the law to install this equipment in certain environments. It is the responsibility of the installation company and end user to comply with state and federal laws. If you are unfamiliar with these laws, consult a qualified attorney.

Warranty

1 year parts and labor.

SPECIFICATIONS

Microphone Specifications

- Omni-directional Electret element. 25' range in all directions.
- Low noise MOSFET pre-amplifier.
- Line level, unbalanced output.
- Adjustable gain.
- Treble boost circuit. Selectable on/off. Enhances clarity of time lapse recordings.
- Limiter circuit. Selectable on/off.
- Easy cable run termination.
- Flush or surface mountable. Can be mounted on a single gang electrical box.
- Power: 12 VDC @ 10mA

Interface Adapter Specifications

- Standard RCA jack for connection to tape recorders, etc.
- Easy cable run termination.
- LED power indicator.
- Power: 12 VDC @ 10mA
- Reverse polarity protected and fused.
- Dimensions W 1.75 x L 2.75 x H 1.25