

DESCRIPTION

This hidden camera contains a Sony 1/3" Super HAD camera. This camera looks more like a real motion detector than any other hidden motion detector on the market today. This unit also has a very flexible mount that makes it easy to get the coverage that you need. This camera also has an excellent low light chipset.



SPECIFICATIONS

Model Name	SCS-826
Image Device	1/3" Color Sony Super HAD
Picture Elements	NTSC:510×492
Resolution	380 TVL
Min. Illumination	0.2 Lux / F 2.0
S/N Ratio	More than 48dB
Electronic Shutter	NTSC:1/60~ 1/100,000
Gamma	0.45
Lens Furnished	Cone Lens 3.7mm / F2.0
White Balance	Auto
Gain Control	Auto
Sync. System	Internal
Video Output	1 Vp-p / 75 Ohms
Audio Output	2 Vp-p / 50 Ohms
Power Supply	DC12V±10%
Power Consumption	2.4W max.
Built-in PIR Sensor	Yes
PIR N.C/N.O Relay Output	AC125V / 1A, DC30V / 2A
PIR N.C/N.O Relay Alarm Time	2~40 sec (Adjustable)
PIR Detection Angle	Hor.=100° / Ver.=45°
PIR Max. Detection Range	10 M
Operating Temp.	-10°C ~ 50°C

Design and specifications are subject to change without notice.